



EVEREST 1100

PURE SINE WAVE POWER STATION

The Everest 1100 has all the power you need to support you on your camping trip. With 1166 watt hours of capacity, the Everest 1100 can power microwave ovenxxs, water cookers, blenders, coffee makers, camping heaters, LCD TV's and power tools up to 1000W power. With multiple outlets and a direct solar panel port, the Everest 1100 is a great addition to long off road getaways.



TOUGH & DURABLE



ADVANCED BATTERY MANAGEMENT



CHARGE VIA SOLAR PANEL



9 LAYERS OF SAFETY PROTECTION



3 X AC OUTLETS

EXAMPLES OF USE



MINI FRIDGES



LAPTOPS & COMPUTERS



E-BIKES & SCOOTERS



POWER TOOLS



LCD TELEVISIONS



CPAP MACHINES

SPECIFICATIONS

*Specifications subject to change

SKU Number	ENPP01100USBL
Size	13.38" x 9.25" x 8.11"
Weight	27.1lbs
Capacity	1166Wh (21.6V/54,000mAh)
AC Output	110V 60Hz, 1000W max (AC ports 1, 2, 3)
DC Output	1 x DC auto outlet 12V=10A / 2 x DC 5.5mm port 12V=5A
USB-A Output	USB 1: QC 3.0, 18W, USB 2: QC 3.0, 18W, USB 3: 5V=2.4A, USB 4: 5V=2.4A
USB-C Output	USB-C 1, PD 100W: 5V=3A/9V=3A/12V=3A/15V=3A/20V=5A, USB-C 2, PD 27W: 5V=3A/9V=3A/12V=2.25A
Input	DC port (6.3mm): 24V=5A, USB-C port: PD 100W: 5V=3A/9V=3A/12V=3A/15V=3A/20V=5A
Material	ABS plastic and polycarbonate
Warranty	24 Months
Special Features	State of Charge (SOC) battery indicator Safety Features: low-voltage, high-voltage, overload, short circuit, reverse connection, hightemperature, fault protection and pure sine wave inverter. LCD display Indicators for errors, charging, fan, temperature warning 94V-0 fire-proof shell

PACKAGE CONTENTS

- 1 x Everest 1100 Portable Power Station
- 1 x AC adapter
- 1 x Car charger cable
- 1 x User manual

