



# EVEREST 1800

## PURE SINE WAVE POWER STATION

The Everest 1800 boasts 1856 watt hours of capacity to keep you powered. The Everest 1800 can power microwave ovens, water cookers, blenders, coffee makers, camping heaters, LCD TV's and power tools up to 1500W power. With multiple outlets and a direct solar panel port, the Everest 1800 is a great addition to long off road getaways when you need that extra bit of power.



TOUGH & DURABLE



ADVANCED BATTERY MANAGEMENT



CHARGE VIA SOLAR PANEL



9 LAYERS OF SAFETY PROTECTION



2 X AC OUTLETS

### EXAMPLES OF USE



MINI FRIDGES



LAPTOPS & COMPUTERS



E-BIKES & SCOOTERS



POWER TOOLS



LCD TELEVISIONS



CPAP MACHINES

## SPECIFICATIONS

\*Specifications subject to change

SKU Number	ENPP01800EUBL
Size	340 x 231 x 276mm
Weight	18.5kg
Capacity	1856Wh (25.6V/72,500mAh)
AC Output	230V/50Hz. Pure Sine Wave 1500W, Peak 3000W
DC Output	1 x DC auto outlet 12V=10A / 2 x DC 5.5mm port 12V=5A
USB-A Output	USB 1: QC 3.0, 18W, USB 2: QC 3.0, 18W, USB 3: 5V=2.4A, USB 4: 5V=2.4A
USB-C Output	USB-C 1, PD 100W : 5V=3A/9V=3A/12V=3A/15V=3A/20V=5A, USB-C 2, PD 27W : 5V=2.4A/9V=3A/12V=2.25A
Input	DC port (6.3mm) : 24V 5A, USB-C port : PD 100W : 5V=3A/9V=3A/12V=3A/15V=3A/20V=5A
Material	ABS plastic and polycarbonate
Warranty	24 Months
Special Features	State of Charge (SOC) battery indicator Safety Features: low-voltage, high-voltage, overload, short circuit, reverse connection, high-temperature, fault protection and pure sine wave inverter. LCD display Indicators for errors, charging, fan, temperature warning 94V-0 fire-proof shell

## PACKAGE CONTENTS

- 1 x Everest 1800 Portable Power Station
- 1 x Charging cable (AC/DC)
- 1 x User manual

