



EVEREST 500

PURE SINE WAVE POWER STATION

The Everest 500 is an easy to carry portable power station with a large capacity of 515 watt hours. With this traveling and working essential, you can also power larger items such as mini-fridges, LCD TV's, food processors, CPAP machines, electric fans, halogen work lights and power tools up to 500W. Perfect for long camping trips or working out back.



TOUGH & DURABLE



ADVANCED BATTERY MANAGEMENT



CHARGE VIA SOLAR PANEL



MULTI-FUNCTION LCD SCREEN & FLASHLIGHT



2 X AC OUTLETS

EXAMPLES OF USE



MINI FRIDGES



LAPTOPS & COMPUTERS



E-BIKES & SCOOTERS



POWER TOOLS



LCD TELEVISIONS



CPAP MACHINES

SPECIFICATIONS

*Specifications subject to change

SKU Number	ENPP00500USBL
Size	10.2" x 6.77" x 6.73"
Weight	12.3lbs
Capacity	515Wh (34.8Ah,14.8V)
AC Output	110V 60Hz 500W max (AC ports 1 & 2)
DC Output	1 x DC auto outlet 12V=10A / 2 x DC 5.5mm port 12V=5A
USB-A Output	USB 1: QC 3.0, 18W, USB 2: 5V=2.4A, USB 3: 5V=2.4A, USB 4: 5V=2.4A
USB-C Output	PD 60W (5V=3A / 9V=3A / 12V=3A / 15V=3A / 20V=3A)
Input	DC port (4mm) : 19V=3.78A, USB-C port : PD 60W (5V=3A / 9V=3A / 12V=3A / 15V=3A / 20V=3A)
Material	ABS plastic and polycarbonate
Warranty	24 Months
Special Features	State of Charge (SOC) battery indicator Safety Features: low-voltage, high-voltage, overload, short circuit, reverse connection, high-temperature, fault protection and pure sine wave inverter LCD display Indicators for errors, charging, fan, temperature warning 94V-0 fire-proof shell

PACKAGE CONTENTS

- 1 x Everest 500 Portable Power Station
- 1 x AC adapter
- 1 x Car charger cable
- 1 x User manual

